Main Distribution Board

მთავარი გამანაწილებელი ფარი



Circuit breaker / Type / Current, A	Cable type end section, mm2/ Cable lenght	CABLE NUMBER	RATED POWER, kW	CURRENT, A	PHASE	Name of the consumer/ Destination
QF 3P/C 160A	N2XH 5x50 -	M-DP1.1			A,B,C	Shield KDP (level -2.85)
QF 3P/C 25A	N2XH 5x2.5 -	M-DP1.1			A,B,C	Shield DP1.1 (level +0.00)
QF 3P/C 32A	N2XH 5x4 -	M-DP2.1			A,B,C	Shield DP2.1 (level +0.00)
QF 3P/C 32A	N2XH 5x4 -	M-FDP1.0			A,B,C	Shield FDP1.0 (level -2.85)
QF 3P/C 40A	N2XH 5x6 -	M-FDP2.0			A,B,C	Shield FDP2.0 (level +5.32)
QF 3P/C 40A	N2XH 5x6 -	M-FDP3.0			A,B,C	Shield FDP3.0 (level +8.87)
QF 3P/C 40A	N2XH 5x6 -	M-FDP4.0			A,B,C	Shield FDP4.0 (level +12.48)
QF 3P/C 125A	N2XH 5x35 -	M-NDB1.0			A,B,C	Shield NDB1.0 (level 5.32)
QF 3P/C 125A	N2XH 5x35 -	M-NDB2.0			A,B,C	Shield NDB2.0 (level +8.87)
QF 3P/C 125A	N2XH 5x25 -	M-NDB3.0			A,B,C	Shield NDB3.0 (level +12.48)
QF 3P/C 63A	N2XH 5x10 -	M-AHUDP			A,B,C	Shield AHUDP (level +0.00)
QF 3P/C 450A	N2XH 4X150+1X95 -	M-H&CDP			A,B,C	Shield H&CDP (level 16.32 on the roof)
QF 3P/C 63A	N2XH 5X10 -	M-Pump			A,B,C	Pump room
QF 3P/C 63A	-				A,B,C	Spare
QF 3P/C 25A	-				A,B,C	Spare
QF 3P/C 16A	-				A,B,C	Spare

Circuit breaker / Type / Current, A	Cable type end section, mm2/ Cable lenght	CABLE NUMBER	RATED POWER, kW	CURRENT, A	PHASE	Name of the consumer/ Destination
QF 1P/C 50A	NHXH FE180/E30 3x6 -	M-Rack			A	RACK
QF 1P/C 125A	NHXH FE180/E30 3x35 -	M-FPR			B	Fire Pump room
QF 3P/C 32A	NHXH FE180/E30 5x4 -	M-Vent1			A,B,C	Fire Ventilator1
QF 3P/C 16A	NHXH FE180/E30 5X1.5 -	M-Vent2			A,B,C	Fire Ventilator2
QF 3P/D 50A	N2XH 5x10 -	M-EL1			A,B,C	Elevator №1
QF 3P/D 50A	N2XH 5x10 -	M-EL2			A,B,C	Elevator №2
QF 3P/D 50A	N2XH 5x10 -	M-EL3			A,B,C	Elevator №3
QF 3P/C 32A	N2XH 5x4 -	M-EL4			A,B,C	Elevator №4 for kitchen
QF 3P/D 32A	-				A,B,C	Spare
QF 3P/C 16A	-				A,B,C	Spare
QF 1P/C 16A	-				C	SPARE

CASA CALDA
Georgia, Tbilisi 0160
56 Lubliana Street
Tel./Fax: (995 32) 2 311 525
(995 32) 2 311 525
E-mail: casacalda@yahoo.com
info@casacalda.ge
www.casacalda.ge

ცვლილებათა ჩამონათვალი

N	თარიღი	აღწერა

პროექტის დასახელება

Gagarini Hotel
გაგარინის ქუჩა. სასტუმრო

დამკვეთი

პროექტის მისამართი

პოზიცია	სახელი/გვარი	ხელმოწერა
ელექტრო ინჟინერი	კოზა გელეშვილი	

ფურცლის დასახელება
Electical Supply
ელექტრო მიწოდებები

ფურცლის ნომერი		რევიზია
EE-01		
პროექტირების ეტაპი	ფორმატი	თარიღი
	A1	